
Contact Us

Support, replacement part ordering, and service may be arranged by contacting our Cincinnati office. Parts for service can be returned following request of a Return Material Authorization.

CTI Products, Inc.
1211 W Sharon Rd
Cincinnati, OH 45240

513-595-5900
support@ctiproductions.com

Disclaimer

Information in this document is provided with best efforts for completeness and accuracy. However, no guarantee is expressed or implied, and details may change without notice.

Fonts used in this document:

Technical terms

Cross-references within this document

[Hyperlinks to other documents or web pages](#)

Warnings

Notes and important information

Software buttons, menus, menu options, folders, and pages

Software parameter values

Contents

RADIOPRO DISPATCH OVERVIEW	6
STARTUP	7
EXAMPLE CONFIGURATION	7
TOOLBAR	8
AUDIO CONTROLS	8
<i>Initial Settings</i>	8
<i>Mic Audio Transmit Slider and VU Meter</i>	8
<i>Select and Unselect Audio Sliders</i>	9
QUICK MAP, ARCHIVE, AND REPORTS TOOLBAR BUTTONS	10
TOOLBAR BUTTONS FOR CUSTOM ACTIONS	10
DISK STORAGE CAUTION SYMBOL	10
EMERGENCY EVENTS	10
<i>Indicators</i>	10
<i>Operation</i>	10
<i>Clearing an Emergency State of a Control Station Radio</i>	10
VOICE TAB(S)	11
MAKING A VOICE CALL TO A TALK GROUP	11
<i>Transmit Indicators</i>	11
<i>Adjusting Transmit Volume</i>	11
<i>Patching</i>	11
RECEIVING A CALL	12
<i>Adjusting the Receive Volume</i>	12
<i>Receive Indicators</i>	12
CONNECTION STATUS INDICATORS	12
<i>Radio Disconnected</i>	12
<i>Can't Connect to Gateway</i>	12
GPS MAP TAB(S)	13
SUBSCRIBER DETAILS	13
SUBSCRIBER ACTIONS	14
<i>Select a Subscriber</i>	14
<i>Make a Private Call</i>	14
<i>Send a Text Message</i>	14
TOOLBAR BUTTONS	14
<i>Subscriber Visibility Button</i>	14
<i>Center (Subscribers on Map) Button</i>	14
<i>Follow (the Visible Subscribers) Button</i>	14
<i>Map Presets Button</i>	14
<i>Map Type Button</i>	15
MORE MAP FEATURES	15
<i>Place Markers</i>	15
<i>Quick Reports</i>	15
SUBSCRIBERS PANEL	16

MAKING A GROUP OR PRIVATE CALL	16
SUBSCRIBER ACTION BUTTONS	16
<i>GPS Locate</i>	16
<i>Radio Check</i>	16
<i>Call Alert</i>	16
<i>Remote Monitor</i>	17
<i>Remote Enable and Disable</i>	17
SEARCHING FOR A SUBSCRIBER	17
SORTING THE SUBSCRIBER LIST	17
 GEO-FENCE ALERTS PANEL	18
 RECENT HISTORY PANEL.....	18
 MISSED CALLS PANEL.....	18
 MESSAGES PANEL	19
MAIN MESSAGE VIEW	19
CONVERSATION VIEW	19
 MENUS.....	20
FILE MENU	20
<i>Change User</i>	20
<i>Open</i>	20
<i>Edit</i>	20
<i>Exit</i>	20
OPTIONS MENU	20
<i>Manage Devices</i>	20
<i>Audio Presets</i>	21
<i>Update License</i>	21
<i>Contacts</i>	21
HELP MENU	22
<i>About</i>	22
<i>Remote Support</i>	22
<i>Logs</i>	22
<i>ARS / GPS Events</i>	22
 QUICK MAP	23
SELECTED SUBSCRIBER	23
TOOLBAR	24
<i>Zoom Tools</i>	24
<i>Map Type Tool</i>	24
<i>Map Presets Tool</i>	24
<i>GPS Locate Tool</i>	24
<i>Text Messaging Tool</i>	24
<i>PTT Tool</i>	24
 ARCHIVE VIEWER.....	25
SEARCH FILTERS AREA	25
<i>Quick Filter Bar</i>	25
<i>Preset Time Intervals</i>	25

Custom Time Interval 26

Event Type(s) 26

Custom Search Criteria 26

Search Button 27

SEARCH RESULTS AREA 27

Records Found 27

Search Target Date 27

Records Found List 27

EVENT DETAIL AREA 28

Voice Recording Detail 28

Subscriber GPS Location Detail 28

PAGE NAVIGATION AREA 28

WHAT IF **29**

What if One Radio Controller is Grayed-out? 29

What if All Radio Controllers are Grayed-out? 30

What if the Transmit Error Window is displayed? 31

FEATURE AVAILABILITY **33**

Motorola MOTOTRBO Systems 33

Kenwood NEXEDGE Systems 33

INDEX **34**

RADIOPRO DISPATCH OVERVIEW


The IP Gateways interface the radio system to an IP network. One IP Gateway is required for each control station radio used for voice. The IP Gateways and control station radios can be centrally located or scattered among different locations using a Virtual Private Network (VPN) or Wide Area Network (WAN) such as the Internet.

Each IP Gateway in a RadioPro system acts as the server for the Control Station Radio connected to it, and ensures easy wide-area deployment. Since there is not a server PC, the architecture reduces "single point-of-failure" concerns.

A system may have a mixture of RadioPro Dispatch, Solo, and Talk clients for PCs, as well as RadioPro Talk for Mobile apps running on mobile devices. These Clients may be centrally located or scattered among different locations using a Virtual Private Network (VPN) or Wide Area Network (WAN) such as the Internet.

RadioPro Dispatch offers a console-type solution for applications requiring connection to many **NEXEDGE** or **MOTOTRBO** radios (control stations). It is designed with an intuitive user interface to minimize learning time and maximize a user's efficiency. A host of accessories are available to implement an enterprise solution; including desk microphones, headsets, footswitches, and touch screens – all with PTT capabilities. Depending on the license purchased, features of RadioPro Dispatch may include:


- Voice Dispatching for 1 to 40 Talk Groups
- GPS Mapping of radio subscriber units
- Text Messaging
- Voice and Event Logging and Playback
- Telemetry



STARTUP

To start the RadioPro Dispatch client, double-click the **RadioPro Dispatch** icon on the PC desktop.

When the **Login** window is displayed as shown at right, choose a **User** from the drop-down list, and then click the **Login** button.




EXAMPLE CONFIGURATION

When the RadioPro Dispatch Client opens, the Main Window will be displayed with various tabbed panels:

- Radio Controllers (voice)
- Map
- Subscribers
- Recent History
- Text Messaging
- Geo-fence Alerts
- Missed Calls

These tabbed panels can be docked in alternate positions or hidden completely if not needed. The **Main Window** on the PC monitor may look different than the example shown below, depending on how your System Administrator configured the tabbed panels within the RadioPro Dispatch client user interface.



TOOLBAR

The **Toolbar** contains tools for **Audio levels**, as well as standard and custom buttons as described below.

Audio Controls


Initial Settings

Use the audio sliders on the **Toolbar** to adjust audio levels for **Mic** transmit audio, **Select** receive audio and **Unselect** receive audio. A VU meter is located next to the **Mic** audio slider to visually determine the loudness of outgoing transmissions.

Begin by selecting an **Audio Preset** from the **Options Menu**. **Audio Presets** may be configured by the System Administrator for various audio devices including speakers, microphones, and headsets. A default preset uses the PC's default selection for microphone and speakers.

Make initial volume settings as follows:

- In the **Toolbar**, adjust the **Mic** and **Select** sliders to 100%, and the **Unselect** slider to 50%.
- In each **Radio Controller**, click on the speaker tool, and adjust the slider to 100%.
- If desk speakers are installed for receive audio, use the control knob on the desk speakers to adjust the overall speaker volume to 50%.



Mic Audio Transmit Slider and VU Meter

Various microphones and headsets may be connected to the Dispatch PC for transmitting audio. Only one active device can be used at any given time, determined by the selection in **Options . . . Audio Presets**.

While clicking on a PTT button, speak into the microphone or headset and view the microphone audio level displayed on the VU meter (located on the **Toolbar** next to the **Mic** slider). For optimum sound level, the meter should reach into the yellow area 10-50% of the duration. The red area indicates clipping and distortion, and should be avoided. To adjust **Mic** volume level, click and drag the slider to the desired level.

If a headset is being used, it may also have a volume adjustment.

System Administrator Adjustment

If a wider range of adjustment is needed, the System Administrator can adjust the microphone transmit audio level by right-clicking the speaker tool in the Windows system tray to display the Operating System Volume Mixer.




- For Windows 8 and Windows 7, choose **Recording Devices** from the drop-down list. On the **Recording** tab, double-click the appropriate microphone, and then adjust the slider on the **Levels** tab.
- For Windows XP, choose **Open Volume Control**. In the **Master Volume** window, choose **Properties** from the **Options** menu. In the **Mixer Device** list, select the appropriate microphone, and then click the **OK** button. Adjust the slider to **100%**.

Select and Unselect Audio Sliders

One or more Radio Controllers can be *Selected* to have their audio received at the *Select* audio level, determined by the **Select** volume slider that is located in the **Toolbar**.

To adjust **Select** or **Unselect** volume levels, click and drag the slider to the desired level. Typically, the **Select** audio will be set at 100%, and the **Unselect** audio will be set at a value less than 100%.

There are various ways to adjust incoming volume:

- For any **Radio Controller**, click on the speaker tool  in the **Radio Controller** window header to show the volume slider for this radio channel. Click and drag the slider to the desired level. Double-click the speaker tool to toggle between mute and un-mute states.
- To adjust *Select* and *Unselect* volume levels, use the **Select** or **Unselect** volume sliders on the **Toolbar**. Click and drag the slider to the desired level.
- If desk speakers are installed, use the Volume knob to adjust the speaker volume.

System Administrator Adjustment



If a wider range of adjustment is needed, the System Administrator can adjust the overall speaker volume by right-clicking the speaker tool in the Windows system tray, then clicking on **Playback Devices** to display the Operating System Volume Mixer. The volume sliders should normally be set to 100%.



The **Toolbar** can hold **Toolbar Buttons** that have been configured by your System Administrator. **Toolbar Buttons** can be defined for a wide range of actions and will have custom labels. A few of the more common uses for **Toolbar Buttons** are described below.

Call Selected

A **Toolbar Button** may be configured to make a call to one or more *Selected* Talk Groups. *Select* a single Talk Group by clicking on the header portion of the Radio Controller. *Select* multiple Talk Groups by holding down the Ctrl key on the keyboard, and clicking on the header portion of various Radio Controllers. (Note that the Radio Controller header will be shaded yellow when *Selected*.)



To make a voice call to the *Selected* channel(s), click and hold the **Call Selected** **Toolbar Button** while speaking into the microphone. If a touch-screen is installed, this can also be done by touching and holding the button on the touch screen. In addition, a pushbutton on a desk microphone or footswitch may have been configured to activate the *Call Selected* function.

All Call

A **Toolbar Button** may be configured to make a call to all radio subscribers in the radio system. To initiate an All Call to every subscriber in the radio system, click and hold the **All Call** **Toolbar Button** while speaking into a microphone or headset. All Call voice messages are queued in memory, and then sent when a channel is clear. This ensures that every subscriber receives the entire message. If a touch-screen is installed, this can also be done by touching and holding the button on the touch screen.




All Emergency

A **Toolbar Button** may be configured to activate the emergency tone on each radio in the system.




Quick Map, Archive, and Reports Toolbar Buttons

The **Toolbar** contains toolbar buttons for **Quick Map**, **Archive**, and **Reports**. Clicking one of these buttons will open a window to view information for those functions. The **Archive** and **Reports** buttons may be grayed out and unavailable if History Logging has not been configured. See later in this document for details on these buttons.



Toolbar Buttons for Custom Actions

The **Toolbar** can hold Toolbar Buttons that have been configured by your System Administrator. Toolbar Buttons can be configured for a wide range of actions and will have custom labels.



Disk Storage Caution Symbol


RadioPro Dispatch continuously calculates the remaining amount of storage on the hard disk partition specified by the System Administrator for logging of Voice files, Text Messages, and other radio system events. If less than two weeks of storage remains on the hard disk partition, a caution symbol will be displayed on the right side of the Main Toolbar. If the hard disk partition becomes full, logging will no longer take place. To allow continued logging, the System Administrator must remove unwanted files, or transfer them to permanent storage media.



Emergency Events

Indicators



When an emergency is initiated from a subscriber, the following indications help to quickly identify the channel and subscriber:


- An Emergency Notification Tool is placed in the Main Toolbar. This tool can be used to respond to the radio user that initiated the emergency. It is also used to clear the emergency.
- A red emergency icon  is visible in the Subscribers Window, next to the subscriber who initiated the emergency.
- An audio alarm signal is activated.



Operation

The following actions can be used to acknowledge an emergency condition by clicking on the emergency tool being displayed in the Toolbar:

- PTT  The top portion of the Emergency Notification Tool in the Toolbar can be used as a PTT to return a private call to the radio user that initiated the emergency. Clicking on this button will silence the audio alarm signal for this emergency, and then place a private call to the radio that initiated the emergency.
- Options  The bottom portion of the Emergency Notification Tool can be used to remove the visual and audio indicators for this emergency.



Clearing an Emergency State of a Control Station Radio


The System Administrator can configure the way in which an emergency state is cleared in the Control Station radio. One option will clear the emergency state when **Remove** is selected from the emergency drop-down list as shown above.

Another method requires that the Control Station radio be manually reset after an Emergency has been **Removed** (cleared). This is accomplished by using the following steps:

1. From the **Options** menu, choose **Manage Devices**.
2. Right-click the radio where the emergency state must be cleared, and then choose **Restart Radio**.

VOICE TAB(S)

Voice tabs hold Radio Controllers and are customized by your System Administrator to show optional features such as radio programmable buttons and status information. Radio Controllers can also be customized with border colors to help organize and highlight certain radio Talk Groups.







Making a Voice Call to a Talk Group

To initiate a voice call to an entire radio Talk Group, use the **PTT** button on a **Radio Controller Window**. Use the PC's mouse to click and hold the **PTT** while speaking into a microphone or headset. If a touch-screen is installed, touch and hold the **PTT**. In addition, a PTT pushbutton on a desk microphone or footswitch may have been configured to activate a call to a particular Talk Group.

Transmit Indicators


When a PTT is activated on a Radio Controller, the following indications are visible:

- The **PTT** button background color changes to red.
- The **Transmitting** icon  is displayed.
- The icon for either a **private call**  or **group call**  is displayed.
- Text is displayed to indicate the Radio ID or Group ID as well as the alias name of the subscriber or group.



Adjusting Transmit Volume


Use the **Mic** audio slider on the **Toolbar** to adjust the transmitted audio. A VU meter is located next to the **Mic** audio slider to visually determine the loudness of outgoing transmissions.



Patching

If enabled by the System Administrator, the **Patch** button will be added to the header of the Radio Controller, enabling the creation of a patch between a pair of Talk Groups. When a patch is created, transmit and receive voice traffic will be shared by both Talk Groups. In addition, a voice call placed by the dispatcher to one of the patched Talk Groups will be heard by both Talk Groups in the patch.



To create a patch, click the  button (until it is highlighted as shown at right) on the two Radio Controllers that are to be patched together. Patching is limited to a single pair of Talk Groups for the entire RadioPro system.

If this option is enabled for Radio Controllers on other Dispatch clients, patch status will be displayed on these other clients.

Receiving a Call




Adjusting the Receive Volume

Click the speaker tool in the header portion of the Radio Controller to make an adjustment to the receive-audio level for a Talk Group. Double-click the speaker tool to switch the audio level between muted and un-muted.



Receive Indicators

When a call is received, the Radio Controller will indicate the following:


- The **Receiving** icon  is displayed.
- The icon for either a **private call**  or **group call**  is displayed.
- Text is displayed to indicate the Radio ID or Group ID as well as the alias name of the subscriber or group.



Connection Status Indicators


Radio Disconnected

When an IP Gateway cannot communicate with the connected Control Station radio, the Radio Controller background is shaded dark gray, and "Radio Disconnected" is displayed.



Can't Connect to Gateway


When the RadioPro Dispatch client cannot communicate with the connected IP Gateway, the Radio Controller background is shaded dark gray, and "Can't connect to Gateway" is displayed.



GPS MAP TAB(S)

GPS map tabs are configured during installation and occupy a space on the desktop determined by the System Administrator. They can be configured to be docked to the Main Window using tabs or can be configured to be undocked in separate windows. The GPS map tab shown below shows the following features:


- Geo-fence 6 Polygon 16 outlined in green is a geo-fence that defines the city limits.
- Geo-fence 6 Route 16 outlined in pink is a geo-fence that defines a route.
- Location 6 A green circle denotes the current location for radio subscriber 9083.
- Trail Crumbs 6 The blue line is the route taken by this subscriber. Hover the mouse over any grey circle on this route to display the date and time that this subscriber was at this location.
- Subscriber Status Bar 6 Information is displayed at the bottom of the GPS map tab for the selected subscriber including current speed (or duration of stop), street address, and time since last GPS update.




Subscriber Details

Select a subscriber, either by clicking a subscriber icon on the map or by choosing a subscriber in the **Subscribers** panel. Note that the current position of the selected subscriber is a green circle to indicate movement, or a red stop sign to indicate stopped. Notice that Trail Crumbs are shown for this selected subscriber for the last 30 minutes. (This time is configurable by the System Administrator using the **Edit** mode.) Hover over any waypoint (grey circle) on a subscriber's route to show date, time, and speed at this point.

View detailed information for this subscriber in the **Subscriber Status Bar** located at the bottom of the map. Information will include street address, rate of travel (or stopped time), and time since last GPS update.

Click the  icon to open **Google Street View** to see the features that a subscriber could see at this location.

Click the  icon to copy the information in the **Subscriber Status Bar** to the Windows **Clipboard**. This information may then be pasted into other applications, such as email, text messaging, and Microsoft Office.

Subscriber Actions

Select a Subscriber

Select a subscriber, either by clicking on an icon on the map or a subscriber in the *Subscribers* tab.

Make a Private Call



Use the **PTT** button at the bottom of the **Subscribers** tab to make a private call to this subscriber.




Send a Text Message


While a subscriber is selected, the **Text** tab can be used to send a private text message to this selected subscriber.

Toolbar buttons


Subscriber Visibility Button

Click the **Visibility**  button to select which subscribers should be visible on the selected map. A window will be displayed that looks very similar to the *Subscribers* tab. However, the **Visible Subscribers** tab adds control for visibility. Visibility may be toggled on and off individually by clicking a subscriber's visibility  icon as shown at right, or as a group by clicking the icon for that group. Three versions of this symbol will indicate visibility as indicated below:


Symbol	Groups	Subscribers
	All members are visible	Subscriber is visible
	Some members are visible	
	No members are visible	Subscriber is not visible




Center (Subscribers on Map) Button

Click the **Center**  button to zoom and reposition the map in order to show all visible subscribers on the selected map.


Follow (the Visible Subscribers) Button

Click the **Follow**  button to keep the selected subscriber centered in the selected map.

Map Presets Button

Click the top portion of the **Map Presets**  button to return the selected map to the indicated preset as configured by the System Administrator.

Click the arrow on the lower portion of this button to list other presets that have been configured by the System Administrator. Click on one of the items in the list to switch the selected map to a new preset.




Map Type Button



Click the **Map Type** button to list Map Types that have been enabled by the System Administrator.

More Map Features

Right-click a point on the GPS map to display the menu shown at right.



Place Markers


Choose **Add Place Marker** to add a marker to the map. Using the Add Place Marker window, customize the marker for marker Display Name, Radius, and color. A marker with the chosen parameters will be shown on the GPS map.

Choose **Clear Place Markers** to remove all Place Markers from this GPS map.



Quick Reports


When a subscriber is selected, choose **Quick Reports** to show the menu options for reports for this subscriber. Available reports include **Position Report** and **Stopped Report**.



SUBSCRIBERS PANEL


The **Subscribers** panel lists radio subscriber and subscriber groups. In addition to the Radio ID, the list may also contain alias names for radio subscribers.

The **Subscribers** tab may also contain buttons to perform specific functions as described below.



Making a Group or Private Call


To initiate a group or private voice call using the **Subscribers** tab, select a Group or Private subscriber, and then click and hold the **PTT** button at the bottom of this window while speaking into a microphone or headset. Alternatively, if a touch-screen is installed, touch and hold the **PTT** button on the screen.



Subscriber Action Buttons

Additional subscriber actions are available at the bottom of the Subscribers tab, including the following.


GPS Locate



Click the **GPS Locate** button to locate the selected subscriber. After clicking this button, the Quick Map icon on the Toolbar will display a count-down to locate the radio subscriber. If a GPS response message is received from the subscriber radio, the Quick Map window will open, and the subscriber will be positioned at the center of the map.




Radio Check



indicate the subscriber's availability.

Click the **Radio Check** button to determine if a radio is accessible, and the talk group or channel currently being used. A **Check Radio** window will be displayed to




Call Alert




Click the **Call Alert** button to activate the alert tone on a subscriber radio. The alert tone will sound on the subscriber radio until the user responds to it.

Remote Monitor





Click the **Remote Monitor** button to remotely key-up a subscriber radio. This function must be enabled in the subscriber radio to allow this function. If function is enabled, the radio will key-up for a period of time configured in the radio.


Remote Enable and Disable





Click the **Remote Disable** button to power down a subscriber radio and cause it to be unable to power up. Click the **Remote Enable** button to remove this restriction for a subscriber radio.




Searching for a Subscriber


Click the  tool near the top of the Subscribers tab to show the Search box. Type characters in the Search box for a subscriber radio ID or an alias name. Click the  tool to clear the typed characters from the Search box.



Sorting the Subscriber List

Click the  tool near the top of the Subscribers tab to sort the subscriber list numerically by **Radio ID**. Click it again to sort in reverse order. Note that the button changes to  and indicates a reverse order sort.

Click the  button to show a list of sorting options; ðSort by IDð and ðSort by Nameð. When ðSort by Nameð is selected, the sort button changes to , or  for reverse sorting.



GEO-FENCE ALERTS PANEL


One or more Geo-fences may exist in order to check various conditions of radio subscribers. One or more conditions may exist for each geo-fence. The conditions can apply to **All Subscribers** or **Specific Subscribers**. When a Geo-fence condition is met for a radio subscriber, an event is logged in the database. In addition, Geo-fence conditions that are true are listed in the **Geo-Fence Alerts** panel. A typical listing of Geo-fence Alerts is shown below.

Geo-fence Alert	Subscriber	Geo-fence	Time Length
Speeding	9084	<Everywhere>	
Speeding	9082	<Everywhere>	58s
Speeding	9085	<Everywhere>	2s
Speeding	9086	<Everywhere>	
Speeding	9085	<Everywhere>	

RECENT HISTORY PANEL

The **Recent History** panel includes the most recent events of the radio system, including voice calls, text messages, call alerts, and emergencies. The number of events displayed in this window can be configured by your System Administrator, between 1 and 500.

- To replay audio, click a voice event (indicated by a speaker tool), and then click the Play button at the top of this window. If the Play button and the Note button are grayed-out, the selected audio event has not been logged to the hard disk because **History Logging** has not been configured. In this case, the System Administrator must configure **History Logging** using the **Dispatch Settings** window, found in the **Options** menu.
- An alternative method for replaying audio is to double-click a voice event that appears in the **Recent History** tab.
- Add a note to an event by clicking the button to open the **Note** window. Only the last note added for an event will be displayed in the **Recent History** window.
- The events in the **Recent History** tab can be sorted by clicking on one of the headings.




MISSED CALLS PANEL

The **Missed Calls** panel will display a list of incoming private calls that have not been responded to from the Dispatcher with a return private call. When a private call is made from the Dispatcher to a subscriber in this list, the subscriber will be removed from the list.

Additional functions are available from the **Missed Calls** panel:

- To cancel a missed call that is listed, select a subscriber from the **Missed Calls** list and then click the Cancel Missed Call button.
- To play the last incoming audio from a subscriber, select a subscriber from the **Missed Calls** list and then click the **Play Audio** button.
- To return a private call to a subscriber, select the subscriber from the **Missed Calls** list and then click the **Call** button.





MESSAGES PANEL


Use the **Messages** panel to send and receive text messages between this PC and a radio users. It is designed to function similar to messaging found on a smart mobile device. Two views are available.

Main Message View

Main Message View is the default view and shows the last conversation for each radio subscriber, with the most current conversation at the top.

A conversation can be started by clicking the  button. In the **New Text Message** box, choose one or more recipients, and choose an option for **When to send** from the drop-down list. Finally, type the message, and then click the  button. The new message will be displayed in the **Main Message View** as a conversation. Message status displayed along with the message include:


- Sending
- Pending
- No acknowledgement





A message that was sent successfully will display the elapsed time from being sent.

Conversation View

Click one of the conversations on the **Main Message View** to see the details of a **Conversation**. In the **Conversation View**, all messages with the selected radio or radio group will be displayed, along with status information for each message.

Use the  button to go back to the **Main Message View**.

To add a reply to this conversion, type the reply into the **Enter Message** text box, and then press the  button.



MENUS

File Menu

Change User

Click on **Change User** to open the **Login** window, and allow another user to log into the system.



Open

Configuration files contain customized screen layouts that can be used for different users of the RadioPro Dispatch client software. Click on **Open** in the **File** menu to load a saved configuration file.

Edit

The **Edit** menu item is used by the System Administrator to customize the operation and screen layout of the RadioPro Dispatch client software.

Exit

Click on **Exit** in the **File** menu to exit the RadioPro Dispatch client.

Options Menu

Manage Devices

The **Manage Devices** window displays the status of connections to radio resources. The settings in this window can be altered only by the System Administrator.

Status Table

Table headings in the Manage Devices window are defined as follows:

Address	Name	Gateway Status	Radio Status	Date Time
198.144.43.102.48222	Public 4 LTR	Connected - 5.1.10	01.07.02	12/18/2012 3:56:37
10.0.0.120.48222	Town River	Connected - 5.1.9	Radio not connected	12/18/2012 3:46:20
198.144.43.99.48222	Public 1 Digital	Connected - 5.1.10	01.08.10	12/18/2012 3:56:35
198.144.43.100.48222	Public 2 Analog	Connected - 5.1.10	01.07.00	12/18/2012 3:56:35
198.144.43.101.48222	Public 3 Connect	Connected - 5.1.10	01.11.16	12/18/2012 3:56:35

System Problems

Description
 1 radios not connected to gateway.
 One or more gateways not in sync with time server.

Address

IP Address assigned to IP Gateway, and Port Number.

Name

Name assigned to IP Gateway.

Gateway Status

Indicates **Connected** and firmware version of IP Gateway, or **Not Connected**.

Radio Status

Indicates firmware version of Radio if connected, or **Not Connected**.

Date / Time

Date and Time being used by IP Gateway.

Record Option

When checked, allows logging of audio to the database.

Audio Option

When checked, allows audio to be heard for this IP Gateway.

Text Option

When checked, this option allows text messaging for this IP Gateway.

Actions

The following actions are available by right-clicking on an entry in the Status Table.

- **Restart Radio** will restart the Control Station radio connected to the selected IP Gateway
- **Restart Gateway** will restart the selected IP Gateway. The **Gateway Status** will be indicated as **Not Connected** for approximately two minutes. Following this period of restarting, verify that the IP Gateway and Radio indicate a proper connection status.

System Problems Box

The **System Problems** box at the bottom of the window will describe current system faults, such as unconnected Radio Resources and License limits.

Audio Presets

Audio Presets may be configured by the System Administrator for various audio devices including speakers, microphones, and headsets. A default preset uses the PC's default selection for microphone and speakers. All configured Audio Presets will be listed, with the selected preset indicated with a check mark.

Update License

When not in **Edit** mode, the **Update License** window can be viewed, but cannot be altered. It will show the **USB Key ID #**, and licensed options.



To export the license file for archiving to another location, click the **Export** button, and then choose a file name and location.



Contacts

Click on **Contacts** from the **Options** menu to open the **Subscriber Contacts** window. This window can be used to add, delete, or edit alias names and other information related to a Radio ID. It can also be used to create groups of radio subscribers for better organization within the Subscribers window. This information will be displayed in the **Subscribers** tab.

Editing the Contacts List

Use the right side of the **Subscriber Contacts** window to make changes to contacts. Click the  button to add a contact to the list. Click the  button to delete a contact from the list. This information will be displayed in the **Subscribers** tab.




Table headings in this window are defined as follows:

ID

Subscriber Radio ID (digital channel) or MDC code (analog channel)

Type

Subscriber type: Digital Group, Digital Private, MDC Group (analog channel), or MDC Private (analog channel).

Alias



Alias name associated with a Subscriber Radio ID


Assigned Channel

<Automatic> (default normal mode) allows the system to dynamically assign an IP address of a Radio Resource. Alternately, a Radio Resource may be permanently assigned to this Subscriber Radio ID using an IP Address and Port Number.

Managing Groups

Use the left side of the **Subscriber Contacts** window to make changes to Groups. Click the  button to add a new Group.

Click the  button to delete a Group. Click the  button to edit a group's name. This information will be displayed in the **Subscribers** tab.




Saving the Contacts List

Click the **Save** button to save changes to the Contacts and Groups. Changes will be saved to a file named:

aliasTable.csv

This CSV (Comma Separated Values) file can be viewed and edited directly using Microsoft Excel by using the link at the bottom left corner of the **Subscriber Contacts** window. When saving this file from Microsoft Excel, be certain to save it as a CSV file.



Help Menu

About

Click on **About** in the **Help** menu to display Part Number and Version of the RadioPro Dispatch client.

Remote Support

If difficulties are experienced with RadioPro Dispatch and the console PC has Internet access, use this option to assist our Technical Support department in remotely logging into the PC.

Logs

This feature is used by CTI personnel only.


ARS / GPS Events

This feature is used by CTI personnel only.

QUICK MAP



Click the Quick Map button on the **Toolbar** to open the **Quick Map** GPS window. An example Quick Map is shown below.



Selected Subscriber

One subscriber may be **Selected** by clicking on its label. When a subscriber is **Selected**, its label (including radio ID or alias name) will be emphasized, and the following actions are available:

- Make a Private call to the subscriber. (See **PTT Tool** below.)
- Send a Private Text Message to the subscriber/ (See **Text Messaging Tool** below.)
- View the Snap-to-Road route traveled by the subscriber.
- View Time-stamp at a location and Speed of Subscriber by hovering over any Trail Crumb.

Toolbar

The **Toolbar** for the **GPS Window** contains tools for **Zooming**, **Map Type**, **Map Presets**, **GPS Locate**, **Text Messaging**, and **PTT**.

Zoom Tools

Use the Zoom In and Zoom Out tools, or optionally, use the mouse scroll wheel for zooming.




Map Type Tool

Your System Administrator may have configured optional Map Types to be available. Click this tool to display these optional Map Types including Roads, Satellite, and Hybrid.




Map Presets Tool

Your System Administrator may have configured optional Map Presets in order to quickly jump to various geographic locations with a predetermined zoom setting. Multiple Map Presets may be configured.




GPS Locate Tool

This tool duplicates the function of the **GPS Locate** button located in the **Subscribers** tab. Before clicking this tool, select a Subscriber from the **Subscriber List**. Click the **GPS Locate** button to locate the selected subscriber. After clicking this button, the **GPS Locate** tool will change to the **Locating** tool, with information relating to the selected subscriber. When the subscriber is located, the GPS window will open, and the subscriber will be positioned at the center of the GPS map.



Text Messaging Tool

Use this tool to send a text message to the subscriber selected on either the **GPS Map Window**, or in the **Subscribers** tab. After clicking this tool, the **Send Text Message** window will be displayed as shown at right.




PTT Tool

Use this tool to make a private call to the subscriber selected on either the **GPS Map Window**, or in the **Subscribers** tab. Click and hold this tool for the duration of the call.




ARCHIVE VIEWER

The Archive Viewer may be opened using either of the following methods:

- To open the embedded version of the Archive Viewer from RadioPro Dispatch client, click the Archive tool  on the Toolbar.
- During installation of RadioPro Dispatch, the stand-alone ArchiveViewer.exe is copied to the installation folder.
From the folder: C:\Program Files (x86)\RadioPro\
copy the file named: ArchiveViewer.exe
to a PC that requires access to the RadioPro database.

The **Archive Viewer** has major sections indicated below; *Search Filters*, *Search Results*, *Event Detail*, and *Page Navigation Bar*.



Search Filters Area

The *Search Filters Area* of the **Archive Viewer Window** allows very flexible searching of the database and display of the search results using the features described below.

Quick Filter Bar


The **Quick Filter Bar** contains tools to easily find archive events based on day, time, user, radio channel, or event type.

Preset Time Intervals

The **Preset Time Intervals** allow various selections such as "Today", "Yesterday", "This Week", "Last Week" and others. To specify a Preset Time Interval, click the





button, and then choose an interval from the drop-down list



Custom Time Interval


Custom **Start Time** and **End Time** may be specified for time periods that are not in the **Preset Time Intervals** list. To specify a




Custom Time Interval, click the  button, choose **Custom Interval** from the drop-down list, and then complete the **Start Time** and **End Time** fields.

Event Type(s)


One or more Event Types may be selected as part of the search criteria. Click the **All** button to quickly select all event types. If a search is performed with no Event Type selected, the search will include *all* Event Types.



Click the **Notes Only** button to search only for events that have Notes attached to them. Notes are attached to an event by clicking the **Note** button  on the **Recent History** tab.

Custom Search Criteria

Use the Custom Search Criteria box to enter specific details about the events to be found. Searchable items include Gateway name, Channel name, Zone name, Alias name, and Alias ID number. The following are some guidelines for search criteria:



- **Separate each search detail with a space.**
- **Any Terms** vs. **All Terms**: If **Any Terms** is selected, searching for *õBob Northö* will return all results where either *õBobö* or *õNorthö* is found. If **All Terms** is selected, searching for *õBob Northö* will return all results where *õBobö* and *õNorthö* is found in a single record.
- **Search criteria are NOT case sensitive.** For example, a search for *õNorthö* is the same as searching for *õNORTHö* or for *õNoRtHö*.
- **Wild card character (*)**: The wild card character can be used to search for zero or more characters after the end of a search item (and only at the end). Correct search criteria include *õBobö*, or *õB*ö*. **Incorrect** search criteria include *õB*bö*, or *õ*obö*.
- **Double quotes (õ ö)**: Searching for a phrase using double quotes, such as the Gateway name *õFire Northö* (including the space between the two words), will find the entire phrase within the double quotes.
- **Special characters**: Any special characters used in naming will be logged to the database. However, special characters cannot be used as search criteria.

Search Examples

Correct search criteria to locate Gateway name *Fire North* include:

- *Fire*
- *North*
- *Fire North* (space between Fire and North)
- *North Fire* (space between North and Fire)
- *õFireö õNorthö*
- *F**
- *F* N** (space between F* and N*)
- *õfire northö*

Incorrect search criteria include: *Fire:North*, *Fir*, *Nor*, *õNorth Fireö*, *FireNorth*, **orth*, *No*th*.

Search Button

Click the **Search** button to perform a search for all parameters selected in the Search Filter Area.



Search Results Area

The Search Results Area will display the records that match the search criteria specified in the Search Filters Area. The various sections of the Search Results Area are described below.

A screenshot of the Search Results Area showing a table of records for Tuesday, December 11, 2012. The table has columns for Description, i message, Gateway, Channel, Zone, and Ch / Zn. The records are: Maintenance - Walt (9083), Maintenance - Judy (9084), Traffic (9085), Security 1 (9081), and Security 234 (9082).

Description	i message	Gateway	Channel	Zone	Ch / Zn
Maintenance - Walt (9083)	(39.11, -84.51), 30.00 mph	12:00 AM	Public 1 Di.	Zone 2	1/1
Maintenance - Judy (9084)	(39.04, -84.61), 50.00 mph	12:00 AM	Public 1 Di.	Zone 2	1/1
Traffic (9085)	(39.16, -84.52), 25.00 mph	12:00 AM	Public 1 Di.	Zone 2	1/1
Security 1 (9081)	(39.17, -84.45), 40.00 mph	12:00 AM	Public 1 Di.	Zone 2	1/1
Security 234 (9082)	(39.03, -84.48), 60.00 mph	12:00 AM	Public 1 Di.	Zone 2	1/1

Records Found

This parameter displays the number of Records Found that match the search criteria.

Search Target Date

This parameter displays the Date for the Records displayed.

Records Found List

This section lists the Records Found that match the search criteria.



Event Detail Area

The Event Detail Area lists specifics about the event that is selected in the Search Results Area, and will change depending if the selected event is a Voice Recording, Subscriber GPS Location, Text Message, or Geo-fence Event.

Voice Recording Detail

If the selected event is a Voice Recording, the Voice Play Tool will be displayed.





Click the Play Button  to begin the playback of the selected Voice Recording. Click the Speaker Button  to display the Audio Playback Level slider.


Subscriber GPS Location Detail

If the selected event is a Subscriber GPS Location, a Toolbar will include Zoom Tools, Map Type Tool, and Map Presets Tool. In addition, a map will display subscriber details and location for the archived event.



Page Navigation Area


Click  or  to view the previous or next page of events, or click on a number to view that page.



WHAT IF . . .

What if One Radio Controller is Grayed-out?

Example Screenshot



One Radio Controller is grayed-out and not connected

Significance


When one Radio Controller is darkened as indicated above, it could mean any of the following:

- The network connection between the PC and the IP Gateway has been lost, indicated by "Can't connect to Gateway".
- The IP Gateway is either turned off or is in the process of rebooting.
- The Control Station radio is either disconnected from the IP Gateway, is turned off, or is in the process of rebooting, indicated by "Radio Disconnected".

Details

Further detail about the connection to an IP Gateway is available by using the information in the [Manage Devices](#) window as follows:

- From the **Options** menu, choose **Manage Devices**.
- In the **Manage Devices** window shown below, the **Gateway Status** will be indicated either as "Connected" or "Not Connected". In addition, the **Radio Status** will be indicated as either "Connected" when its version is displayed, or "Radio not connected".



Corrective Actions

Gateway Status is "Connected" and Radio Version is "Radio not connected"

- Verify that the Control Station radio is powered on.


- Verify that the Control Station radio is physically connected to the IP Gateway using the supplied cable.
- Verify that a programming cable is **NOT** connected to the front mic connector of the Control Station radio. If a programming cable is connected to the front mic connector, remove it, and then reboot the radio.

Gateway Status is “Not Connected” and Radio Version is “Radio not connected”

- Verify that power is connected to the IP Gateway.
- Verify that the blue Power light on the front of the IP Gateway is illuminated.
- Verify that the IP Gateway is accessible to the RadioPro software by using the Ping function from a Windows command prompt.
- Look into the left-side vent holes of the IP Gateway and observe the red LED:
 - A non-blinking LED indicates that the IP Gateway has completed its rebooting sequence and is running normally.
 - A blinking LED indicates that the IP Gateway is rebooting. Rebooting should be completed within 2 minutes. If rebooting is not completed within 2 minutes, return unit to CTI Products for repair.

What if All Radio Controllers are Grayed-out?

Example Screenshot



All Radio Controllers are grayed-out and not connected

Significance

When all Radio Controllers are darkened as indicated above, it could mean any of the following:

- Power has been removed from all IP Gateways.
- The network connection between the PC and the IP Gateways has been lost.
- A USB Hardware Key is not installed in the PC.
- A Software License that matches the USB Hardware Key is not installed.

Corrective Actions

Power has been removed from IP Gateways

- Verify that the IP Gateways have power and are powered on.

Network Connection has been Lost

- Verify that the IP Gateways are accessible to the RadioPro software by using the Ping function from a Windows command prompt.


- Verify that the IP Gateway is accessible to the RadioPro software by using the ICU.exe utility.

A USB Hardware Key is not installed

- Verify that the USB Hardware Key is installed.
- Remove the USB Hardware Key and verify that the Windows alert tone for USB disconnection is heard.
- Re-insert the USB Hardware Key and verify that the Windows alert tone for USB connection is heard.


Software License is not installed or is incorrect


- Verify that a correct Software License is installed by using the following steps:
 - From the **Options** menu, choose **Update License**.
 - In the **Update License** window, verify that the **USB Key Id** matches the serial number engraved on the USB Hardware Key.
 - In the **Update License** window, verify that **Connections** is correct for the number of Radio Controllers.

What if the Transmit Error Window is displayed?***Example Screenshot******Significance***

The above window may be displayed when a PTT button is activated, and if the microphone selected for transmitting is not connected. This can occur if a microphone has been disconnected from the Dispatch PC, or if a microphone has been replaced by another microphone.

Corrective Actions**Determine if a microphone is connected**

- Determine if the Windows operating system recognizes a microphone connected to the PC by using the following steps:
 - In the Windows System Tray located at the lower-right corner of the Windows screen, right-click on the  tool, and then choose **Recording devices**. The following **Sound Recording** properties window will be displayed.



- If the microphone does not appear in the above window, ensure that it is connected to the PC.
- If the microphone appears in the above window, speak into the microphone and notice the response of the sound level indicator. The Sound Level Indicator should reach at least 50% with normal voice volume.

Check Microphone Configuration in RadioPro Dispatch Client

- With the microphone connected, it is possible that the configuration in the RadioPro Dispatch client is incorrect. Use the following steps to verify correct configuration:
 - From the **Options** menu, choose **Audio Presets**, and then verify that the correct preset is selected.
 - Retest the microphone function in RadioPro Dispatch. If needed, ask the System Administrator to continue with the remaining steps.
 - From the **File** menu, choose **Edit**.
 - From the **Options** menu, choose **Audio Presets**, and then choose **Config**.
 - Click on the **Devices** tab to display the following window.



- In the **Devices** tab shown above, verify that the **Mic In** parameter is correct for the Preset being examined.
- Click **Save Settings** to exit the **Audio Configuration** window.

FEATURE AVAILABILITY

Motorola MOTOTRBO Systems

Depending on MOTOTRBO System Type, some features may not be available. Use the following table to determine if a feature discussed in this document is not available.

<i>System Type</i> <i>Feature</i>	<i>Analog</i>	<i>Conv. Digital</i>	<i>Cap +</i>	<i>IP Site Connect</i>	<i>Linked Cap +</i>	<i>Connect Plus</i>	<i>Cap Max</i>
Voice Dispatch	✓	✓	✓	✓	✓	✓	✓
Text Messaging		✓	✓	✓	✓		✓
GPS Mapping		✓	✓	✓	✓		✓
ARS		✓	✓	✓	✓		
Private Call		✓	✓	✓	✓	✓	✓
Remote Monitor		✓	✓	✓	✓	✓	✓
Remote Enable/Disable		✓	✓	✓	✓	✓	✓

Kenwood NEXEDGE Systems

Depending on NEXEDGE System Type, some features may not be available. Use the following table to determine if a feature discussed in this document is available.

<i>System Type</i> <i>Feature</i>	<i>Analog</i>	<i>Analog w/ FleetSync</i>	<i>Digital NXDN</i>	<i>Digital NXDN w/ call ack.</i>	<i>NXDN & LTR Trunking</i>	<i>NXDN Trunking (Mssg Trnkd)</i>
Voice Dispatch	✓	✓	✓	✓	✓	✓
Text Messaging		✓	✓	✓	✓	✓
GPS Mapping		✓	✓	✓	✓	✓
Status Updates		✓	✓	✓	✓	✓
Selective Calling		✓	✓	Not Currently Supported	✓	Not Currently Supported
Remote Monitor		✓	✓	✓	✓	✓
Remote Enable/Disable		✓	✓	✓	✓	✓

INDEX

A

Add Note Button, 9, 17, 18, 26
Alias Name, 21
 Alias Table, 22
 All-Call Tool Button, 9
 All-Emergency Button, 9
 Archive Map, 25
 Archive Viewer Window, 25
 Assigned Channel, 21
 Audio Preset, 8, 21, 32

C

Call Alert Button, 16
 Call Select Tool Button, 9
 Change User, 20
 Connected, 20, 21, 29, 30
 Control Station Radio, 6, 10
 CSV Format (comma separated values), 22
 Custom Time Interval, 26

D

Devices Tab, 32
 Dispatch Settings, 18

E

Emergency, 9, 10
 Event Types, 26
Notes Only, 26

G

Geo-fence, 18, 28
 Geo-fences, 28
 GPS Locate Tool Button, 16, 24
 GPS Mapping, 23, 24
 Groups, 6, 9, 11, 21, 22

I

IP Gateway, 6, 12, 20, 21, 29, 30, 31

K

Key
 USB Hardware, 30, 31

L

Levels Tab, 8
 License

Export, 21

Update, 21, 31

USB Key, 21

Login, 7, 20
 Logs, 22

M

Manage Devices Window, 10, 20, 29
 Map Presets Tool Button, 24, 28
 Map Type Tool Button, 24, 28
 Menu
 File, 20
 Help, 22
 Options, 8, 20

O

Overview, 6

P

Page Navigation Bar, 25
 Patch, 11
 Play Button, 28
 Preset Time Interval, 25, 26
 Private Call, 23
 PTT Tool Button, 23, 24

Q

Quick Filter Bar, 25

R

Radio Check Button, 16
 Radio Controller, 8, 9, 11, 12, 29, 30, 31
 Radio Controller tab, 7
 Radio Disconnected, 12, 29
 Radio ID, 11, 12, 17, 21
 Recent History tab, 7, 18, 26
 Records Found, 27
 Remote Disable Button, 17
 Remote Enable Button, 17
 Remote Monitor Button, 17
 Reports, 10
Restart Gateway, 21
 Restart Radio, 10, 21

S

Search Target Date, 27
 Show Console, 22
 Snap-to-Road Route, 23
 Sorting, 17

Subscriber Contacts, 21, 22
Subscriber List Sub-folder, 17, 24
Subscribers tab, 16

Receive, 12
Select Receive, 8, 9
Unselect Receive, 8, 9

T

Text Messaging, 6, 7, 24
Tool Bar, 8, 9, 10, 11, 23, 24, 25, 26, 28
Tool Buttons, custom, 9, 10
Toolbar, 8, 9, 10, 11, 23, 24, 25, 26, 28
Toolbar Buttons, custom, 9, 10
Transmit Error, 31

W

Warning
Disk Storage Caution, 10

X

XPR4550, 10

V

Version, 1, 22, 29, 30
Virtual Private Network, 6
Voice and Event Logging, 6, 10, 18
Volume Adjustments

Z

Zoom, 24, 28