

## Focused on the Future

Over 7x faster processing speed and 15x more memory capacity than the previous models, these new NEXEDGE repeaters represent a breakthrough in performance. Extensive data storage means they can support everything from analog/digital conventional systems up to a highly sophisticated NEXEDGE Generation2 (Gen2) multi-site digital trunked network. And further adding to their future-proof credentials is upcoming support for Digital Simulcast. Stay ahead of the curve, with cutting-edge communications.

### GENERAL FEATURES

- Wideband Coverage
- 25/5/0.5 W RF Output Power (100% Duty Cycle)
- Two-Digit Numeric Display
- LED Status Indicators
- USB 2.0 Type-B Interface
- IP LAN/WAN Connectivity
- Ethernet Network Interface
- 6 Programmable Function Keys
- 0.3 W Front Panel Speaker
- 3 W External Speaker Audio
- Volume Control
- Program / Modem Interface
- Remote Termination Interface
- Programmable AUX I/O's
- DTMF Remote Control
- Flash Firmware Upgrading
- Remote System Firmware Updates
- Telephone Interconnect Option

### DIGITAL – GENERAL

- NXDN Digital Air Interface
- AMBE+2™ VOCODER
- 6.25 & 12.5 kHz Bandwidth
- Built-In 0.5 ppm TCXO
- UID & GID Validation
- NXR Over-the-Air Alias
- SNMP Protocol Ready
- FER (Frame Error Rate) / RSSI Output

### DIGITAL – TRUNKING MODE

- NEXEDGE Gen2 Network
  - \* NXDN Type-C Trunking (Gen1) will be supported later
- Transmission Trunked Mode
- Message Trunked Mode
- Busy Call Queuing
- Call Queue Pre-emption
- Late Entry (UID & GID)
- Control / Traffic Channel Switching
- Control Channel Rotation
- Cross-Busy
- Failsaft Mode

- NXDN Traffic Channel Sharing
- ESN Validation
- Auto-Roaming / Registration
- Wide Area All Group Call

### DIGITAL – CONVENTIONAL MODE

- Mixed FM / Digital Operation
- Conventional IP Networks
- Site Roaming Capability
- Digital Voting
- RF Link
- Digital Simulcast (To be supported in future)

### FM ANALOG MODE

- 16 QT/DQTs Repeater Control Built-in
- Hang Timer / Time Out Timer / CW ID
- External FM Controller Interface
- EIA Voter Tone Generation
- External LTR® Controller Interface
- External MPT1327 Controller Interface



**KMC-35**  
Microphone



**KTI-4M**  
Telephone Interconnect Adapter



All accessories and options may not be available in all markets. Contact our authorized dealer for details and complete list of all accessories and options.

## Main Specifications

GENERAL		NXR-5700	NXR-5800
<b>Frequency Range</b>	Type 1 Type 2	136-174 MHz -	450-520 MHz 400-470 MHz
<b>Channel Spacing</b>	Analog Digital	30*/25*/15/12.5 kHz 12.5/6.25 kHz	25*/12.5 kHz
<b>PLL Channel Step</b>		6.25/5/3.125/2.5 kHz	6.25/5/3.125 kHz
<b>Operating Voltage</b>		13.6 V DC (10.8 - 15.6 V DC)	
<b>Operating Temperature Range</b>		-22° F ~ +140° F (-30° C ~ +60° C)	
<b>Frequency Stability</b>		± 0.5 ppm	
<b>Antenna Impedance</b>		50 Ω	
<b>Dimensions (W x H x D)</b>	Projections Not Included	19.02 x 1.73 x 13.03 in (483 x 44 x 331 mm)	
<b>Weight (net)</b>		11 lb (5 kg)	
<b>FCC ID</b>	Type 1 Type 2	K44474500 -	K44474600 K44474601
<b>IC Certification</b>	Type 1 Type 2	282F-474500 -	- 282F-474601

\*25 and 30 kHz are not included in the models sold in the USA or US territories. Measurements made per CAI measurement procedures (digital) and TIA-603 (analog); specifications are typical. Details and timing of firmware and software updates are subject to change without notice. Specifications are subject to change without notice, due to advancements in technology.

LTR® is a registered trademark of EFJohnson Technologies.  
AMBE+2™ is a trademark of Digital Voice Systems Inc.  
NXDN® is a trademark of JVCKENWOOD Corporation and Icom Inc.  
NEXEDGE® is a registered trademark of JVCKENWOOD Corporation.

RECEIVER		NXR-5700	NXR-5800
<b>Sensitivity</b>	Digital @ 6.25 kHz (3% BER) Digital @ 12.5 kHz (3% BER) Analog (12 dB SINAD)		0.27 μV 0.33 μV 0.30 μV
<b>Selectivity</b>	Analog @ 30*/25* kHz Analog @ 12.5 kHz	92 dB (± 30 kHz) 84 dB (± 12.5 kHz)	86 dB (± 25 kHz) 80 dB (± 12.5 kHz)
<b>FM Hum &amp; Noise</b>	Analog @ 30*/25* kHz Analog @ 12.5 kHz		55 dB 50 dB
<b>Intermodulation Distortion</b>	Analog	85 dB (± 50/100 kHz)	
<b>Spurious Response</b>	Analog	100 dB	
<b>Audio Distortion (Ext.SP)</b>		Less than 2% (at 0.3 W)	
<b>Audio Output (Ext.SP)</b>		3 W (at 4 Ω Less than 5 % distortion)	
TRANSMITTER			
<b>RF Power Output High / Low</b>		25/5/0.5 W	
<b>RMax Duty Cycle</b>		100%	
<b>Spurious &amp; Harmonics</b>		73 dB	
<b>FM Hum &amp; Noise</b>	Analog @ 30*/25* kHz Analog @ 12.5 kHz		55 dB 50 dB
<b>Audio Distortion</b>		Less than 1% at 1000 Hz	
<b>Emission Designator</b>		16K0F3E, 11K0F3E, 8K30F1E, 8K30F1D, 8K30F7W, 4K00F1E, 4K00F1D, 4K00F7W, 4K00F2D	

## Applicable MIL-STD

MIL Standard	MIL 810C Methods/Procedures	MIL 810D Methods/Procedures	MIL 810E Methods/Procedures	MIL 810F Methods/Procedures	MIL 810G Methods/Procedures
<b>High Temperature</b>	501.1/Procedure I, II	501.2/Procedure I, II	501.3/Procedure I, II	501.4/Procedure I, II	501.5/Procedure I, II
<b>Low Temperature</b>	502.1/Procedure I	502.2/Procedure I	502.3/Procedure I	502.4/Procedure I	502.5/Procedure II
<b>Temperature Shock</b>	503.1/Procedure I, II	503.2/Procedure I, II	503.3/Procedure I, II	503.4/Procedure I, II	503.5/Procedure I

# KENWOOD

JVCKENWOOD USA Corporation  
Communications Sector Headquarters  
3970 Johns Creek Court, Suite 100, Suwanee, GA 30024-1265  
Order Administration/Distribution  
P.O. BOX 22745, 2201 East Dominguez St., Long Beach, CA 90801-5745  
[www.kenwood.com/usa](http://www.kenwood.com/usa)

JVCKENWOOD Canada Inc.  
Canadian Headquarters and Distribution  
6070 Kestrel Road, Mississauga, Ontario, Canada L5T 1S8  
[www.kenwood.com/ca](http://www.kenwood.com/ca)



ISO9001 Registered  
JVCKENWOOD Corporation